

# Step 4 - Add charger (general step)

You can now add the charger in the blue navigation bar under the E-Mobility tab. The name will help you find it later. For example, "ABB Terra on PP 01".

It is very important and essential to enter the serial number of the charging station correctly, for example, "TACW22-4-1021-Gxxx".

Connection ID: The standard is usually 1 (this selection is intended for charging stations with multiple connections).

Plug type: Choose between AC Type 2 or CCS

Connection name: Here you can save the name "CCS Left", for example, for a DC charger with multiple charging points.

Performance: A charging station may be limited to 11 kW on the hardware side. Enter the correct value here.

When saving, the following prompt appears: "A charger must be added to a location". Select the object you created in step 2. Under Documentation, you also have the option of adding images to the charging station.

grafik.png

*Tip: To test whether the charging station has been successfully integrated into the portal, press "Charger overview". Here you can now select your charging station and the last connection should now be displayed under "Last received data". If you see data that is a few minutes old here, the integration has been successful.*

After a short time, the charging station should show the successful online status with the

green icon. If a charging station is offline for a certain period of time, the icon will change to red.

grafik.png

---

Revision #4

Created 17 January 2025 08:44:28 by David Brouwer

Updated 11 March 2025 11:33:12 by David Brouwer